## 145E1-27.5-SD

220 Watt, non isolated, single output buck converter with internal decoupling diode All parameters defined on Ta=25°C, IoNom = 8,0 ADC and UiNom = 48VDC

## **ABSOLUTE MAXIMUM RATINGS**

| parameter   | unit | typ    |
|---|------|--------|
| Input peak voltage                                    | VDC  | 120.00 |
| Feedback protection against overvoltage on the output | VDC  | 55     |
| Output overvoltage protection                         | VDC  | 35.0   |

## **THERMAL CHARACTERISTICS**

| -40°C / +85°C |                                |
|---------------|--------------------------------|
|               | +90°C                          |
| -10°C/+65°C   |                                |
|               | 75% RH                         |
|               | 25                             |
|               | -40°C / +85°C<br>-10°C / +65°C |

## **COMMUNICATION INTERFACE**

| parameter                                  | unit | fulfilled    | conditions | min to max  |
|--|------|--------------|------------|-------------|
| Option shut down (left open for operation) |      | $\checkmark$ |            |             |
| Shutdown voltage for transformer           | VDC  |              | loNom      | -0,2 to 2,8 |

### **SPECIALS**

| parameter                               | unit | fulfilled    | conditions    | typ       |
|---|------|--------------|---------------|-----------|
| Switching frequency                     | kHz  |              |               | 140       |
| Efficiency at light loads               | %    |              | 0.25loNom     | 94.00     |
| Efficiency at medium loads              | %    |              | 0.5loNom      | 95.00     |
| Efficiency at full loads                | %    |              | loNom         | 93.00     |
| MTTF                                    | h    |              | SN29500 @ 70° | 1 300 000 |
| For active loads or parallel connection |      | $\checkmark$ |               |           |
| Drives high capacitive loads            |      | $\checkmark$ |               |           |
| CC/CV battery load characteristic       |      | $\checkmark$ |               |           |
| Insulation strength primary to case     | VDC  |              |               | 1500      |

### **COMPLIANCE**

| fulfilled    | notes   |
|--------------|---|
| $\checkmark$ |   |
|              | fulfilled<br>√<br>√<br>√<br>√<br>√<br>√<br>√<br>√<br>√<br>√ |

All technical and general information is provided in all conscience. However, completeness and accuracy cannot be guaranteed. Demke recommends to fully test the product in its determined application. Due to permanent improvements to our products, we reserve the right to change specifications at any time and without prior notification and without obligation to update products already supplied. This is a component for professional equipment manufacturers. Read the safety and installation instruction for proper use. Safety aspect and EMC-aspect must be considered in the end application.



Demke Electronic GmbH **Tonhallestrasse 37** 9500 Wil • Switzerland

phone +41 71 511 34 00 e-mail sales@demke-electronic.com

web www.demke-electronic.com

## **TECHNICAL DATASHEET**

### 145E1-27.5-SD

220 Watt, non isolated, single output buck converter with internal decoupling diode

55022<A

All technical and general information is provided in all conscience. However, completeness and accuracy cannot be guaranteed. Demke recommends to fully test the product in its determined application. Due to permanent improvements to our products, we reserve the right to change specifications at any time and without prior notification and without obligation to update products already supplied. This is a component for professional equipment manufacturers. Read the safety and installation instruction for proper use. Safety aspect and EMC-aspect must be considered in the end application.



Demke Electronic GmbH Tonhallestrasse 37 9500 Wil • Switzerland

phone +41 71 511 34 00 e-mail sales@demke-electronic.com

## **TECHNICAL DATASHEET**

## 145E1-27.5-SD

#### 220 Watt, non isolated, single output buck converter with internal decoupling diode

| INPUT<br>parameter                                | unit | conditions | min | typ  | max |
|---|------|------------|-----|------|-----|
| Input voltage range                               | VDC  | loNom      | 30  | 48   | 100 |
| No load input current                             | mA   | UiNom      |     | 18   |     |
| Max. input current                                | А    | UiNom      |     | 8    |     |
| Input start up voltage                            | VDC  | UiNom      |     | 23.5 |     |
| Undervoltage lockout                              | VDC  | UiNom      |     | 21.5 |     |
| Input quiescent current in shutdown mode          | mA   | UiNom      |     | 1.50 |     |
| Input current overshoot during soft start ramp up | %    | loNom      |     | 50   |     |

### OUTPUT

| unit | conditions         | min typ max                                |  |
|------|--------------------|--|--|
| VDC  | loNom              | 27.5                                       |  |
| %    | UiNom              | 0  |  |
| %    | loNom              | +/-2,00%                                   |  |
| %    | loNom              | overdamped                                 |  |
| W    |                    | 220  |  |
|      | VDC<br>%<br>%<br>% | VDC IoNom<br>% UiNom<br>% IoNom<br>% IoNom |  |

### CONTROL

| parameter   | unit | conditions       | min typ  | max |
|---|------|------------------|----------|-----|
| Dynamic load change adjusting time                      | ms   | LoadChange 1090% | 0.40     |     |
| Dynamic load change deviation to nominal output voltage | ٧    | LoadChange 1090% | 2.00     |     |
| Maximum admissible capacitive load                      | uF   | loNom            | infinite | 9   |
| Initial switch on time                                  | ms   | loNom            | 50       |     |
| Softstart ramp up time                                  | ms   | loNom            | 10       |     |
| Restart time after undervoltage lockout                 | ms   | loNom            | 50       |     |

All technical and general information is provided in all conscience. However, completeness and accuracy cannot be guaranteed. Demke recommends to fully test the product in its determined application. Due to permanent improvements to our products, we reserve the right to change specifications at any time and without prior notification and without obligation to update products already supplied. This is a component for professional equipment manufacturers. Read the safety and installation instruction for proper use. Safety aspect and EMC-aspect must be considered in the end application.



Demke Electronic GmbH Tonhallestrasse 37 9500 Wil • Switzerland

# **TECHNICAL DATASHEET**

## 145E1-27.5-SD


220 Watt, non isolated, single output buck converter with internal decoupling diode


### **MECHANICAL**

| parameter          | unit |          |
|--------------------|------|----------|
| Overall dimensions | mm   | 77x52x19 |
| Weight             | g    | 165      |

| Pin No. | Function | <b>Electrical Determination</b> |
|---------|----------|---------------------------------|
| 1       | SD       | Shut down                       |
| 2       | Vi+      | Input voltage positive          |
| 3       | Vi-      | Input voltage negative          |
| 4       | Vo-      | Output voltage negative         |
| 5       | Vo+      | Output voltage positive         |

Mechanical dimensions and Pin configuration All dimensions in mm Connector type: CCA 2,5/5-G-5,08 P26THR Case: FMC 77x52x19





All technical and general information is provided in all conscience. However, completeness and accuracy cannot be guaranteed. Demke recommends to fully test the product in its determined application. Due to permanent improvements to our products, we reserve the right to change specifications at any time and without prior notification and without obligation to update products already supplied. This is a component for professional equipment manufacturers. Read the safety and installation instruction for proper use. Safety aspect and EMC-aspect must be considered in the end application.



Demke Electronic GmbH Tonhallestrasse 37 9500 Wil • Switzerland

phone +41 71 511 34 00 e-mail sales@demke-electronic.com

web www.demke-electronic.com