## **TECHNICAL DATASHEET**

344W-24-SD

50 Watt, isolated, single output buck-boost converter All parameters defined on Ta=25°C, IoNom = 2,0 ADC and UiNom = 80VDC

#### **ABSOLUTE MAXIMUM RATINGS**

parameter	unit	typ
Input peak voltage	VDC	170.00
Feedback protection against overvoltage on the output	VDC	35
Worst case output voltage in fault mode	VDC	29

### THERMAL CHARACTERISTICS

parameter	min to max	typ
Ambient temperature range	-40°C / +85°C	_
Max. case temperature for thermal shut down [°C]		+90°C
Storage temperature (device not in operation)	-10°C / +65°C	_
Relative maximum humidity under storage		75% RH
Storage under worst conditions [in days]		25

#### **COMMUNICATION INTERFACE**

parameter	unit	fulfilled	min to max
Option shut down (left open for operation)		<b>√</b>	

#### **SPECIALS**

parameter	unit	fulfilled	conditions	typ
Switching frequency	kHz			130
Efficiency at medium loads	%		0.5loNom	90.50
Efficiency at full loads	%		loNom	89.50
MTTF	h		SN29500 @ 70°	1 600 000
For active loads or parallel connection		<b>√</b>		_
Drives high capacitive loads		<b>√</b>		
Coupling capacitance input to output	nF			transformer winding only
Insulation strength primary to secondary	VDC			1000

### **COMPLIANCE**

parameter	fulfilled	notes
61000-6-2 (EMC-Immunity standard for industrial environment)	<b>✓</b>	
61000-4-2 (immunity against ESD-electrostatic discharge)	<b>✓</b>	
61000-4-3 (immunity High frequency electromagnetic fields)	<b>✓</b>	
61000-4-4 (immunity against burst - electrical fast transients)	<b>✓</b>	
61000-4-5 (immunity against surge - high energy surges)	<b>✓</b>	
61000-4-6 (immunity against induced, conducted disturbances)	<b>✓</b>	
61000-6-3 (EMC -Emission standard for residential and light		
industry environment)		
55022 <b< td=""><td><b>✓</b></td><td></td></b<>	<b>✓</b>	

All technical and general information is provided in all conscience. However, completeness and accuracy cannot be guaranteed. Demke recommends to fully test the product in its determined application. Due to permanent improvements to our products, we reserve the right to change specifications at any time and without prior notification and without obligation to update products already supplied. This is a component for professional equipment manufacturers. Read the safety and installation instruction for proper use. Safety aspect and EMC-aspect must be considered in the end application.



# **TECHNICAL DATASHEET**

#### 344W-24-SD

50 Watt, isolated, single output buck-boost converter

#### **INPUT**

parameter	unit	conditions	min	typ	max
Input voltage range	VDC	loNom	16	80	160
No load input current	mA	UiNom		16	
Max. input current	Α	UiNom		4	
Input start up voltage	VDC	UiNom		16.7	
Undervoltage lockout	VDC	UiNom		15.5	
Input quiescent current in shutdown mode	mA	UiNom		1.20	
Input current overshoot during soft start ramp up	%	loNom		70	
Generated AC-ripple on the supply (BW=20MHz)	mVp-p	UiNom/IoNom		100	
Generated HF-noise on the supply (BW=20MHz)	mVp-p	UiNom/IoNom		30	

#### **OUTPUT**

parameter	unit	conditions	min typ max
Output voltage	VDC	IoNom	24.0
No Load output voltage increase	%	UiNom	4
Minimum required load to obtain the specified output voltage	%	UiNom	0
Generated AC-ripple on the output (BW=20MHz)	mVp-p	UiNom/IoNom	10
Generated HF-noise on the output (BW=20MHz)	mVp-p	UiNom/IoNom	20
Output voltage accuracy	%	IoNom	+/-2,00%
Output voltage overshoot at initial switch-on	%	IoNom	overdamped
Rated output power	W		50

### **CONTROL**

parameter	unit	conditions mi	in typ	max
Static line regulation	%	IoNom/UiMinUiMax	0.10	
Static load regulation	%	IoMinIoMax/UiNom	0.8	
Dynamic load change adjusting time	ms	LoadChange 1090%	0.70	
Dynamic load change deviation to nominal output voltage	V	LoadChange 1090%	0.13	
Maximum admissible capacitive load	uF	loNom	infinite	
Initial switch on time	ms	loNom	9	
Softstart ramp up time	ms	loNom	4	

All technical and general information is provided in all conscience. However, completeness and accuracy cannot be guaranteed. Demke recommends to fully test the product in its determined application. Due to permanent improvements to our products, we reserve the right to change specifications at any time and without prior notification and without obligation to update products already supplied. This is a component for professional equipment manufacturers. Read the safety and installation instruction for proper use. Safety aspect and EMC-aspect must be considered in the end application.



## **TECHNICAL DATASHEET**

#### 344W-24-SD

50 Watt, isolated, single output buck-boost converter

#### **MECHANICAL**

haramerei	unit		
Overall dimensions	mm	90x90x19	_
Weight	g	230	_


Pin No.	<b>Function</b>	<b>Electrical Determination</b>
1	Vi+	Input voltage positive
2	Vi-	Input voltage negative
3	SD	Shut down
4	NC	Not connected
5	NC	Not connected
6	NC	Not connected
7	Vo-	Output voltage negative
8	Vo+	Output voltage positive

#### **Mechanical dimensions and Pin configuration**

All dimensions in mm

Connector type: CCA 2,5/8-G-5,08 P26THR

Case: 90x90x19



All technical and general information is provided in all conscience. However, completeness and accuracy cannot be guaranteed. Demke recommends to fully test the product in its determined application. Due to permanent improvements to our products, we reserve the right to change specifications at any time and without prior notification and without obligation to update products already supplied. This is a component for professional equipment manufacturers. Read the safety and installation instruction for proper use. Safety aspect and EMC-aspect must be considered in the end application.

